



45715 (ZW3006)

**Z-Wave Interchangeable Paddle
In-wall Dimmer (1000W)**



Key Features

- Turn ON/OFF and control the brightness level of the connected lighting manually or via Z-Wave remote control.
- May be used in single pole installation or with up to three 45710 (ZW2004) auxiliary switches in 2-way, 3-way or 4-way wiring configuration
- Blue LED indicates switch location in a dark room
- Can be Included in multiple Groups and Scenes
- Supports Advanced Configuration; Dim rates, LED status, Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load and Ground. Traveler wire required for multi pole installation
- For use with Incandescent loads only; not intended for use with CFL or LED bulbs
- Use a standard-size wall plate for single gang installations (wall plate not included); Multi-gang box option available (removable 'side wings')
- Interchangeable Paddle switch: White & light almond paddle in package
- LED can be enabled/disabled manually
- Inline traveler circuit protection
- White box contractor packaging
- UL Listed

SPECIFICATIONS

Power: 120 VAC, 60 Hz.

Signal (Frequency): 908.42 MHz.

Minimum Load: 40W

Maximum Load: 1000W, Incandescent

Range: Up to 100 feet line of sight between the Wireless Controller and the closest Z-Wave receiver module.

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only.

cUL Listed

Complies with FCC and Industry Canada regulations

JASCO Products

10 E. Memorial Rd

Oklahoma City, OK 73114

www.jascoproducts.com

www.easyzwave.com

Z-Wave is a registered US trademark of Sigma Designs